



Sir Safety System S.p.A. Single-member company Wholly-owned subsidiary of Sir Holding Srl Via dei Fornaciai, 9 - Santa Maria degli Angeli 06081 Assisi - Perugia - Italy Tel.+39 075.8043737 - Fax +39 075.8048686 VAT Nr. IT 03359340548 Viale Europa 74 20090 Cusago Milano Tel. +39 02.90394575 Fax +39 02.90394441

export@sirsafety.com www.sirsafety.com





Name: Gas alert BW CLIP SO2 Code: FG110001 FG11 ELECTRICAL DEVICES GAS DETECTORS

## **Description**

The gas detector BW Clip SO2 is ideal for those who perform activities in hazardous environments. Operates for up to two years without maintenance: just turn on the device and it runs continuously - no need for calibration, sensor replacement, battery replacement or battery charging.

## It features:

- Maintenance-free: no replacement of sensors or batteries required.
- Compact, lightweightdesign with one-button operation.
- Designed to withstand harsh environments and extreme temperatures.
- Automated self-test of battery, sensor and electronics.
- Wide-angle flash, which alerts simultaneously with audible and vibrating alarm.
- Automatic logging of the 35 most recent gas events and bump test results.
- Water resistant
- Compatible with MicroDock II.
- Introduction of the automatic IntelliDox system which allows faster Bump Tests, reduced gas consumption, optional customisation based on operational needs.

Dimensions: 4,1 x 5,0 x 8,7 cm

Lightweight: 92 g

Humidity: 5% - 95% UR (non-condensing)

Visual, vibrating and acoustic alarm (95 dB); low/high.

Test: Activated detectors automatically perform one internal diagnostic

test every 24 hours.

Ingress Protection: IP 66/67

Certifications: Class I, Div. 1, Group A, B, C, D Class I, Zone 0, Group IIC; II 1G; Ex ia IIC T4

DEMKO 14 ATEX 1356; IECEx: Ex ia IIC T4 IECEx UL 14.0063



Category	Colours	Available Sizes
		Made to order: U In stock:
Quantity/Carton	EC Standards	Important Information
	ATEX  Values:II 1G Ex ia IIC T4 Ga	Suitable to detect the presence of Sulphure Dioxide.
1	IECEX  Values:Ex ia IIC T4 Ga	Make sure the product is in good condition, undamaged and clean before use. Once you become aware of a damage, you should immediately replace it.
		Keep in a cool dry place, far from heat sources.
Dexterity		Storage and cleaning