



Sir Safety System S.p.A. Single-member company Wholly-owned subsidiary of Sir Holding Srl Via dei Fornaciai, 9 - Santa Maria degli Angeli 06081 Assisi - Perugia - Italy Tel.+39 075.8043737 - Fax +39 075.8048686 VAT Nr. IT 03359340548 Viale Europa 74 20090 Cusago Milano Tel. +39 02.90394575 Fax +39 02.90394441 export@sirsafety.com www.sirsafety.com





Name: Gas alert BW CLIP O2 Code: FG110005 FG11 ELECTRICAL DEVICES GAS DETECTORS

Description

The gas detector BW Clip O2 is ideal for those who perform activities in hazardous environments. Operates for up to two years without maintenance: just turn on the device and it runs continuously - no need for calibration, sensor replacement, battery replacementor battery charging.

It features:

- Maintenance-free: no replacement of sensors or batteries required.
- Compact, lightweight design with one-button operation.
- Designed to withstand harsh environments and extreme temperatures.
- Automated self-test of battery, sensor and electronics.
- Wide-angle flash, which alerts simultaneously with audible and vibrating alarm.
- Automatic logging of the 35 most recent gas events and bump test results.
- Water resistant
- Compatible with MicroDock II.
- Introduction of theautomatic IntelliDox system which allows faster Bump Tests, reduced gas consumption, optional customisation based on operational needs.

Dimensions: 4,1 x 5,0 x 8,7 cm

Lightweight: 92 g

Humidity: 5% - 95% UR (non-condensing)

Visual, vibrating and acoustic alarm (95 dB); low/high.

Test: Activated detectors automatically perform one internal diagnostic

test every 24 hours.

Ingress Protection: IP 66/67

Certifications: Class I, Div. 1, Group A, B, C, D Class I, Zone 0, Group IIC; II 1G; Ex ia IIC T4

DEMKO 14 ATEX1356; IECEx: Ex ia IIC T4 IECEx UL 14.0063



Category	Colours	Available Sizes Made to order: U In stock:
Quantity/Carton	EC Standards ATEX Values:II 1G Ex ia IIC T4 Ga IECEX Values:Ex ia IIC T4 Ga	Important Information Suitable to detect the presence of Oxygen. Make sure the product is in good condition, undamaged and clean before use. Once you become aware of a damage, you should immediately replace it.
Dexterity		Keep in a cool dry place, far from heat sources. Storage and cleaning