



SAFETY SYSTEM®
YOUR PROTECTOR

Sir Safety System S.p.A. Single-member company
Wholly-owned subsidiary of Sir Holding Srl
Via dei Fornaciaci, 9 - Santa Maria degli Angeli
06081 Assisi - Perugia - Italy
Tel.+39 075.8043737 - Fax +39 075.8048686

VAT Nr. IT 03359340548
Viale Europa 74
20090 Cusago Milano
Tel. +39 02.90394575
Fax +39 02.90394441

TECHNICAL SHEET

export@sirsafety.com
www.sirsafety.com



UNI EN ISO 9001:2015
UNI EN ISO 14001:2015
UNI EN ISO 45001:2018

| | | |
|--|---------------------|--|
| Name: ONDA banded earplugs 40 pairs | Code: FC1217 | FC12 EAR PROTECTION - REUSABLE EARPLUGS |
|--|---------------------|--|

Description

Banded polyurethane ear plugs. Its particular design helps prevent contact with the work surface. Latex free.
Pack of 40 pairs.

SNR 21 dB
Hertz frequency: H Attenuation = 25
Hertz frequency: M Attenuation = 17
Hertz frequency: L Attenuation = 15
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:63/12.8/ 4.0/8.8;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:125/14.9/3.8/11.1;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:250/24.2/3.8/20.4;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:500/27.7/2.6/25.1;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:1000/25.2/2.1/23.1;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:2000/28.6/2.9/25.7;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:4000/29.3/3.4/25.9;
Freq.(Hz)/Attenuation Med./Dev. standard/Value APV:8000/28.7/4.2/24.5;



The product has been designed and manufactured to comply with Regulation (EU) 2016/425 and subsequent amendments.

| | | |
|--|--------------------------|--|
| Category III | Colours | Available Sizes In stock: U |
| Quantity/Carton 10 | EC Standards EN 352-2 | Important Information Suitable in noisy environments. Make sure the device is in good condition before use. Once you become aware of a damage, you should immediately replace it. Re-usable earplugs. Keep in a cool dry place, far from heat sources. Keep the earplugs clean, so they do not attract dust and dirt before use, promoting proper hygiene in the ear canal. Clean with a damp cloth. Do not use any solvents. |
| Dexterity | | Storage and cleaning |