



**SAFETY SYSTEM®**  
YOUR PROTECTOR

**Sir Safety System S.p.A. Single-member company**  
Wholly-owned subsidiary of Sir Holding Srl  
Via dei Fornaciaci, 9 - Santa Maria degli Angeli  
06081 Assisi - Perugia - Italy  
Tel.+39 075.8043737 - Fax +39 075.8048686

VAT Nr. IT 03359340548  
Viale Europa 74  
20090 Cusago Milano  
Tel. +39 02.90394575  
Fax +39 02.90394441

**TECHNICAL SHEET**

export@sirsafety.com  
www.sirsafety.com



UNI EN ISO 9001:2015  
UNI EN ISO 14001:2015

<b>Name: STARK 11 EARMUFFS</b>	<b>Code: FC1329</b>	<b>FC13 EAR PROTECTION - EAR MUFFS</b>
--------------------------------	---------------------	--

**Description**

Foldable earmuffs with high-density insulation foam. Metal free. Compact when folded for convenient storage.  
Durable headband structure with easy size adjustment that offers great comfort.  
Ideal for all professional users exposed to short-term noise.  
Weight 270 g.

SNR 27 dB  
Frequency in Hz: H Attenuation: 30.2  
Frequency in Hz: M Attenuation: 23.9  
Frequency in Hz: L Attenuation: 17.4  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value: 63/18.5/6.4/12.1  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value: 125/13.9/2.1/11.8  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value: 250/17.9/3.8/14.1;  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value: 500/24.8/4.2/20.6;  
Freq.(Hz)/Attenuation Med./Standard Dev./APV value:  
1000/30.8/2.9/27.9;  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value:  
2000/32.6/3.9/28.7;  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value:  
4000/33.6/2.2/31.4;  
Freq.(Hz)/Attenuation Med./Standard Dev./APV Value: 8000/37.6/33.2.



The product has been designed and manufactured to comply with Regulation (EU)2016/425 and subsequent amendments.

Category <b>III</b>	Colours	Available Sizes <b>U</b>
Quantity/Carton <b>20</b>	EC Standards <b>EN 352-1</b>	Important Information Store in a cool, dry place, away from heat sources. Before use, check that the earmuffs are in perfect condition and replace it if it is not intact. Keep away from impurities before use and between use intervals so that impurities are not transferred into the ear canal. Clean with a damp cloth. Do not use solvents.
Dexterity		Storage and cleaning